



GENERATOARE BRACO SERIA BH (Honda) si BK (Kohler) pe benzina

Motor termic HONDA sau KOHLER SUA

Alternator: Productie Italia

	KOHLER	HONDA	KOHLER	HONDA	KOHLER	KOHLER	KOHLER
Model	BK30 MM	BH60 MM	BK60 MM	BH80 TM	BK80 TM	BK80 ME	BK100 TE
Putere continua (kVA) PRP	2.6	5.7	5.7	7.2/ 3.5	7.2/ 3.5	7.5	9.3/3.5
Putere maxima (kVA) LTP	2.9	6	6	8	8	8	10/3.5
Tensiune iesire (V)	230V	230V	230V	400V/ 230V	400V/ 230V	230V	400V/ 230V
Frecventa (Hz)	50	50	50	50Hz	50Hz	50Hz	50Hz
Factor de putere	1	1	1	0.8/ 1	0.8/ 1	1	0.8/ 1
Alternator	Italia	Italia	Italia	Italia	Italia	Italia	Italia
Motor Tip OHV	KOHLER CH270	HONDA GX390	KOHLER CH440	HONDA GX390	KOHLER CH440	KOHLER CH620	KOHLER CH620
Putere motor(CP)	7	13	14	13	14	18	18
Pornire	sfoara	sfoara	sfoara	sfoara	sfoara	electrica	electrica
Centrimetri cubi c.c.	208	389	429	389	429	624	624
Numar cilindri	1	1	1	1	1	2V	2V
Capacitate ulei	0.6	1.1	1.1	1.1	1.1	1.9	1.9
Capacitate rezervor (litri)	4.1	6.5	7.3	6.5	7.3	25	25
Consum litri/ ora in sarcina 100%	1.5	3	3	3	3	5.5	5.5
Combustibil	benzina	benzina	benzina	benzina	benzina	benzina	benzina
Nivel de zgomot LWA/ dB (A) 7m	97/ 72	99/ 74	99/ 74	99/ 74	99/ 74	99/ 74	99/ 74
Dimensiuni (lxLxh) mm	460x600x400	580x730x520	580x730x520	580x730x520	580x730x520	800x1100x700	800x1100x700
Greutate (kg)	42	75	75	75	75	120	130

Optional

Stabilizator de tensiune electronic AVR

Pornire electrice

Panou de transfer automat AAR